

DH-HAC-HDW1400EM-A

4MP HDCVI IR Eyeball Camera





- * The parameters and datasheets below can only be applied to 1400-S2 series.
- · Max. 30fps@4MP
- · Built-in mic
- · HD and SD output switchable
- · 3.6mm fixed lens (2.8mm, 6mm optional)
- · Max. IR length 50m, Smart IR
- · IP67, DC12V















System Overview

Experience superior 4MP video and the simplicity of reusing existing coaxial infrastructure with HDCVI. The Lite series 4MP HDCVI camera features a compact design and offers a high quality image with rich details at a friendly price. It offers various vari-focal/fixed lens models with a multi-language OSD and HD/SD switchable output. Its structural flexibility and high cost-performance makes the camera an ideal choice for SMB solutions.

Functions

Broadcast-quality Audio

Audio information is used as supplementary evidence in video surveillance applications. The HDCVI camera supports audio signal transmission over coaxial cable. In addition, it adopts unique audio processing and transmission technology that best restores source audio and eliminates noise, guaranteeing the quality and effectiveness of collected audio information.

4 Signals over 1 Coaxial Cable

HDCVI technology supports 4 signals to be transmitted over 1 coaxial cable simultaneously, i.e. video, audio*, data and power. Dual-way data transmission allows the HDCVI camera to interact with the HCVR, such as sending control signal or triggering alarm. Moreover, HDCVI technology supports PoC for construction flexibility.

* Audio input is available for some models of HDCVI cameras.

Long Distance Transmission

HDCVI technology guarantees long-distance and real-time transmission without any loss. It supports up to 700m for 4MP HD video via coaxial cable, and up to 300m via UTP cable.*

*Actual results verified by real-scene testing in Dahua's test laboratory.

Simplicity

HDCVI technology inherits the born feature of simplicity from traditional analog surveillance system, making itself a best choice for investment protection. HDCVI system can seamlessly upgrade the traditional analog system without replacing existing coaxial cabling. The plug and play approach enables full HD video surveillance without the hassle of configuring a network.

Smart IR

The camera is designed with array LED IR illumination for best lowlight performance. Smart IR is a technology to ensure brightness uniformity in B/W image under low illumination. Dahua's unique Smart IR adjusts to the intensity of camera's infrared LEDs to compensate for the distance of an object, and prevents IR LEDs from overexposing images as the object come closer to the camera.

Multi-formats

The camera supports multiple video formats including HDCVI, CVBS and other two common HD analog formats in the market. The four formats can be switched over through OSD menu or by PFM820 (UTC controller). This feature makes the camera to be compatible with not only XVRs but also most end users' existing HD/SD DVRs.

Multi-language OSD

OSD menu provides multiple image adjustments and function settings to meet the requirements of different monitoring scenes. The OSD menu includes configurations such as backlight mode, day/night, white balance, privacy mask and motion detect. The camera supports 11 languages for OSD menu, namely, Chinese, English, French, German, Spanish, Portuguese, Italian, Japanese, Korean, Russian and Polish.

Protection

The camera's outstanding reliability is unsurpassed due to its rugged design. The camera is protected against water and dust with IP67 ranking, making it suitable for indoor or outdoor environments.

With working temperature range of-40 °C to +60 °C (-40 °F to +140 °F), the camera is designed for extreme temperature environments.

Supporting ±30% input voltage tolerance, this camera suits even the most unstable power supply conditions. Its 4KV lightning rating provides protection against the camera and its structure from the effects of lightning.

Lite Series | DH-HAC-HDW1400EM-A

| Technical Specification | |
|--------------------------|--|
| Camera | |
| Image Sensor | 1/2.7" CMOS |
| Effective Pixels | 2560(H)×1440(V), 4MP |
| Scanning System | Progressive |
| Electronic Shutter Speed | PAL: 1/25~1/100000s NTSC: 1/30~1/100000s |
| Minimum Illumination | 0.03Lux/F2.0, 30IRE, 0Lux IR on |
| S/N Ratio | More than 65dB |
| IR Distance | Up to 50m (164feet) |
| IR On/Off Control | Auto / Manual |
| IR LEDs | 1 |
| Lens | |
| Lens Type | Fixed lens / Fixed iris |
| Mount Type | Board-in |
| Focal Length | 3.6mm (2.8mm, 6mm Optional) |
| Max Aperture | F2.0 |
| Angle of View | H: 76.4° (97°/48.6°) V: 41.6° (52°/27.9°) |
| Focus Control | N/A |
| Close Focus Distance | 1400mm (800mm/2500mm) 55.1" (31.5"/98.4") |
| DORI Distance | |

DORI Distance

Note: The DORI distance is a "general proximity" of distance which makes it easy to pinpoint the right camera for your needs. The DORI distance is calculated based on sensor specification and lab test result according to EN 62676-4 which defines the criteria for Detect, Observe, Recognize and Identify respectively.

| | DORI Definition | Distance |
|-----------|----------------------|--|
| Detect | 25px/m (8px/ft) | 2.8mm: 56m(184ft) 3.6mm: 80m(262ft) 6mm: 120m(394ft) |
| Observe | 63px/m (19px/ft) | 2.8mm: 22m(73ft) 3.6mm: 32m(105ft) 6mm: 48m(157ft) |
| Recognize | 125px/m (38px/ft) | 2.8mm: 11m(37ft) 3.6mm: 16m(52ft) 6mm: 24m(79ft) |
| Identify | 250ppm (76px/ft) | 2.8mm: 6m(18ft) 3.6mm: 8m(26ft) 6mm: 12m(39ft) |

Pan / Tilt / Rotation

| | Pan: 0° ~ 360° |
|-------------------|---------------------------------------|
| Pan/Tilt/Rotation | Tilt: 0° ~ 78° Rotation: 0° ~ 360° |

Video

| Resolution | 4MP (2560×1440) |
|------------|------------------------------|
| Frame Rate | 25/30fps@4MP, 25/30fps@1080P |

| Video Output | 1-channel BNC high definition video output / CVBS video output (Can switch) |
|-----------------|---|
| Day/Night | Auto (ICR) / Manual |
| OSD Menu | Multi-language |
| BLC Mode | BLC / HLC / DWDR |
| WDR | DWDR |
| Gain Control | AGC |
| Noise Reduction | 2D |
| White Balance | Auto / Manual |
| Smart IR | Auto / Manual |
| Certifications | |
| Certifications | CE (EN55032, EN55024, EN50130-4) FCC (CFR 47 FCC Part 15 subpartB, ANSI C63.4-2014) UL (UL60950-1+CAN/CSA C22.2 No.60950-1) |
| Interface | |
| Audio Interface | Built-in mic |

Audio Interface

| Eelectrical | |
|-------------------|-------------------------|
| Power Supply | 12V DC ±30% |
| Power Consumption | May 3 9W (12V DC IR on) |

Environmental

| Operating Conditions | * Start up should be done at above-40°C (-40°F) |
|---|---|
| Storage Conditions | -40°C ~ +60°C (-40°F ~ +140°F) / Less than 95% RH |
| Ingress Protection & Vandal Resistance | IP67 |

Construction

| Casing | Aluminium |
|--------------|------------------------------|
| Dimensions | Ф106mm×93.7mm (Ф4.17"×3.69") |
| Net Weight | 0.41kg (0.90lb) |
| Gross Weight | 0.51kg (1.12lb) |

Lite Series | DH-HAC-HDW1400EM-A

| Ordering Information | | | |
|----------------------|---------------------------|--|--|
| Туре | Part Number | Description | |
| 4MP Camera | DH-HAC-HDW1400EMP-A 2.8mm | 4MP HDCVI IR Eyeball Camera, PAL | |
| | DH-HAC-HDW1400EMP-A 3.6mm | | |
| | DH-HAC-HDW1400EMP-A 6mm | | |
| | DH-HAC-HDW1400EMN-A 2.8mm | | |
| | DH-HAC-HDW1400EMN-A 3.6mm | 4MP HDCVI IR Eyeball Camera, NTSC | |
| | DH-HAC-HDW1400EMN-A 6mm | | |
| | PFA130-E | Junction box (For use alone) | |
| | PFB204W | Wall mount (For use alone or with PFA152-E pole mount) | |
| | PFA152-E | Pole mount (For use with PFB204W wall mount) | |
| Accessories | PFM800-4K | Passive Video Balun | |
| Accessories | PFM800B-4K | Passive Video Balun | |
| | PFM321 | 12V 1A Power Adapter | |
| | PFM320D-015 | 12V 1.5A Power Adapter | |
| | PFM300 | 12V 2A Power Adapter | |
| | PFM820 | UTC Controller | |

| 00EMP-A 2.8mm | | | |
|----------------|--|----------------------|--|
| 100EMP-A 3.6mm | 4MP HDCVI IR Eyeball Camera, PAL | | |
| 100EMP-A 6mm | | | |
| 100EMN-A 2.8mm | | | |
| 100EMN-A 3.6mm | 4MP HDCVI IR Eyeball Camera, NTSC | | |
| 00EMN-A 6mm | | | |
| | Junction box (For use alone) | Wall Mount PFB204W | |
| | Wall mount (For use alone or with PFA152-E pole mount) | FFB2U4VV | |
| | Pole mount (For use with PFB204W wall mount) | | |
| | Passive Video Balun | | |
| | Passive Video Balun | | |
| | 12V 1A Power Adapter | | |
| | 12V 1.5A Power Adapter | | |
| | 12V 2A Power Adapter | Dimensions (mm/inch) | |
| | | | |

Junction Mount

PFA130-E

Pole Mount

PFB204W + PFA152-E

Ø106 [Ø4.17"]

Ø69 [Ø2.72"]

4-04.5 [00.18"]

Accessories





PFA130-E Junction box



PFB204W Wall mount



93.7 [3.69"]

PFA152-E Pole mount



PFM800-4K Passive Video Balun



PFM800B-4K Passive Video Balun



PFM321 12V 1A Power Adapter



PFM320D-015 Power Adapter



PFM300 12V 2A Power Adapter



PFM820 UTC Controller

