

# DS-PKA-WLM Wireless Keypad

The DS-PKA-WLM series wireless keypad can connect to security control panel for alarm control and operation. It can also notice alarm by indicator and buzzer.



### **Available Models**

- DS-PKA-WLM-433 (White)
- DS-PKA-WLM-433 (Black)
- DS-PKA-WLM-868 (White)
- DS-PKA-WLM-868 (Black)

### **Features**

- 433/868 MHz two-way wireless communication
- AES-128 encryption
- Operation: Arming, disarming, alarm clearing, etc.
- Arming or disarming with card
- Patrol card (different from the arming/disarming card) checking in
- Full touch screen design with LED backlight





## Specifications

Model		DS-PKA-WLM-433	S-PKA-WLM-868
RF	RF speed	10.0 kbps/4.8 bps	
	RF frequency	433 MHz/868 MHz	
	RF modulation	2GFSK	
	RF distance	800 m (open area)	
	RF power	10 dBm	
Interface & component	TAMPER switch	1	
	RF module	Communicates with wireless control panel	
	Card	Supports standard IC card swiping	
	Buzzer	1	
	Serial port	1, reserved	
	Numeric	10 keys: 0 to 9	
	Function key	6 function keys: fire alarm, away arming, stay arming, disarming, delete, and confirm	
Application & protocol	Protocol	HIK wireless protocol: Access to wireless control panel, two-way communication	
Electrical & battery	Power	3 VDC power input	
	Battery type	4 AA batteries	
	Battery life span	3 years	
Others	Operation humidity	10% to 90% (No condensing)	
	Operation temperature	-10 °C to +55 °C (-4 °F to +122 °F)	
	Color	White or black	
	Dimension	φ131.5 mm (5.2"); height: 23 mm (0.9")	



Distributed by

### **HIKVISION**°

#### Headquarters

No.555 Qianmo Road, Binjiang District, Hangzhou 310051, China T +86-571-8807-5998 overseasbusiness@hikvision.com

Hikvision USA T+1-909-895-0400 sales.usa@hikvision.com

Hikvision Australia T +61-2-8599-4233 salesau@hikvision.com

Hikvision India T +91-22-28469900 sales@pramahikvision.com

Hikvision Canada T +1-866-200-6690 sales.canada@hikvision.com

Hikvision Thailand T +662-275-9949 sales.thailand@hikvision.com Hikvision Europe T +31-23-5542770 sales.eu@hikvision.com

Hikvision Italy T +39-0438-6902 info.it@hikvision.com

Hikvision Brazil T +55 11 3318-0050 Latam.support@hikvision.com

Hikvision Turkey T +90 (216)521 7070- 7074 sales.tr@hikvision.com

Hikvision Malaysia T +601-7652-2413 sales.my@hikvision.com Hikvision UK & Ireland T +01628-902140 sales.uk@hikvision.com

Hikvision South Africa Tel: +27 (10) 0351172 sale.africa@hikvision.com

Hikvision France T +33(0)1-85-330-450 info.fr@hikvision.com

Hikvision Kazakhstan T+7-727-9730667 nikia.panfilov@hikvision.ru

Hikvision Vietnam T +84-974270888 sales.vt@hikvision.com Hikvision UAE T +971-4-4432090 salesme@hikvision.com

Hikvision Singapore T +65-6684-4718 sg@hikvision.com

Hikvision Spain T +34-91-737-16-55 info.es@hikvision.com

Hikvision Tashkent T +99-87-1238-9438 uzb@hikvision.ru

Hikvision Hong Kong T +852-2151-1761 info.hk@hikvision.com Hikvision Russia T +7-495-669-67-99 saleru@hikvision.com

Hikvision Korea T +82-{0}31-731-8817 sales.korea@hikvision.com

Hikvision Poland T +48-22-460-01-50 info.pl@hikvision.com

Hikvision Indonesia T +62-21-2933759 Sales.Indonesia@hikvision.com

Hikvision Colombia sales.colombia@hikvision.com